

Armor Bar Size Chart By Conductor Diameter

Conductor Diameter (mm)	Total Conductor Diameter with Armour Rod (mm)	Armour Rods Diameter (mm)	Rod Quantity	Total Length (mm)	Total Weight (kg)
9,87 -10,54	18,94	4,20	9	1320	0,42
10,55 -11,18	19,58	4,20	10	1370	0,53
11,19 -11,94	20,34	4,20	10	1370	0,53
11,95 -12,65	21,05	4,20	10	1420	0,57
12,66 -13,16	21,56	4,20	11	1420	0,62
13,17 -13,64	22,04	4,20	11	1470	0,62
13,65 -14,35	23,55	4,60	11	1520	0,80
14,36 -14,91	24,11	4,60	11	1620	0,85
14,92 -15,88	25,08	4,60	12	1620	0,93
15,89 -16,66	25,90	4,60	12	1620	0,93
16,67 -17,50	26,70	4,60	13	1730	1,06
17,51 -17,89	28,29	5,20	12	1830	1,20
17,90 -18,80	29,20	5,20	12	1930	1,30
18,81 -19,53	29,93	5,20	13	1930	1,40
19,54 -20,32	33,12	6,40	11	1980	2,00
20,33 -21,49	34,29	6,40	11	2030	2,00
21,50 -23,04	35,84	6,40	12	2130	2,10
23,05 -23,59	36,39	6,40	12	2340	2,30
23,60 -24,97	37,77	6,40	13	2440	2,50
24,98 -26,26	42,06	7,90	11	2540	3,60
26,27 -27,69	43,49	7,90	12	2540	4,00
27,70 -28,96	44,76	7,90	12	2540	4,30
28,97 -30,43	46,23	7,90	13	2540	4,70
30,44 -32,13	50,73	9,30	12	2540	6,00
32,14 -33,78	52,38	9,30	12	2540	6,00
33,79 -35,46	54,06	9,30	13	2540	6,50
35,47 -37,21	59,21	11,00	11	2540	7,70
37,22 -38,86	60,86	11,00	12	2540	8,40
38,87 -40,13	62,13	11,00	12	2540	8,40
40,14 -42,04	64,04	11,00	13	2540	9,10
42,05 -43,95	65,95	11,00	13	2540	9,10
43,96 -45,94	67,94	11,00	14	2540	9,80
45,95 -48,24	70,24	11,00	14	2540	9,80
48,25 -50,59	72,59	11,00	15	2540	10,50
50,60 -53,09	75,09	11,00	15	2540	10,50
53,10 -55,69	79,69	12,00	15	2540	12,00